



Instrument Schedule

Antigone | Guildhall School


Production Electrician: Liam Sayer
E:liamsayer123@gmail.com

LX 1

Chan	Position & Unit#	Multi Loom	Dim	Ckt Name & Cir#	Addr	Purpose	Type & Acc & Load	Clr & Gbo	FIX I/O
(307)	LX 1 #1	LX 1 MULTI	185	THRU-DIM-185	1/185	House Lights	PATT 743+Barndoors 1kW	R371	
(154)	LX 1 #2	LX 1 MULTI	186	THRU-DIM-186	1/186		RJ 614 1kW	L283+ R132	
(136)	LX 1 #3	LX 1 MULTI	187	THRU-DIM-187	1/187		S4 2550 575w	R132	
(136)	LX 1 #3.1	LX 1 MULTI			39/1		Wybron Coloram II 7.5"	Scroll 2	
(145)	LX 1 #4	LX 1 MULTI	188	THRU-DIM-188	1/188	PLATFORM 1	S4 2550 575w	L200+ R132	
(160)	LX 1 #5	LX 1 MULTI	173	THRU-ND-173	31/158		S4L2 50 171w	R119	

SCROLLS:

- 8 Scroll Guildhall: R-53, R-52, R-57, R-366, R-367, R-383, R-82, R-78, R-371, R-372, R-373, R-00, R-02, R-304, R-09, R-14, R-22, R-26, R-313, R-49, R-332, R-79, R-90, R-27





Instrument Schedule
 Antigone | Guildhall School

LX 1

Chan	Position & Unit#	Multi Loom	Dim	Ckt Name & Cir#	Addr	Purpose	Type & Acc & Load	Clr & Gbo	FIX I/O
(165)	LX 1 #6	LX 1 MULTI	189	THRU-DIM-189	1/189		S4 50 575w	L710+ R119	
(15)	LX 1 #7	LX 1 MULTI	174	THRU-ND-174	31/1	REVO	ETC Revolution 750w	R132 + Scroll 1, T:Wheel 3	
(172)	LX 1 #8	LX 1 MULTI	175	THRU-ND-175	31/173		S4L2 CYC 171w	L228	
(3)	LX 1 #9	LX 1 MULTI	176	THRU-ND-176	31/32	MAC III	MAC III 1.5kW	R132	I/O US
(166)	LX 1 #10	LX 1 MULTI	190	THRU-DIM-190	1/190		S4 50 575w	L710+ R119	

SCROLLS:

1. Revolution: R-00, R-52, R-57, R-3220, R-79, R-367, R-78, R-371, R-372, R-373, R-00, R-02, R-09, R-14, R-22, R-36, R-332, R-26, R-313, R-86, R-00



WHEELS:

3. Revolution Gobo: 0: Open, 1: Medium Breakup, 2: Ripple Breakup, 3: Linear 9